



**2006-2012 Model Test RPM Data
Supplement to MIC Stationary Sound Test Manual
for Off-Highway Motorcycles, ATVs, & ROVs**

ARCTIC CAT ATVs / ROVs									
Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			2006	2007	2008	2009	2010	2011	2012
50	50 2X4, DVX	AC10	3250		3250	3250			
90	90 2X4, DVX	AC20	3650	3650	3650	3650	3650	3650	3650
150	150 2X4	AC30				3875	3875	3875	3875
250	250 2X4, DVX	AC50	3200	3200	3200	3200			
300	300 DVX, 2x4	AC60				3750	3750	3750	3750
350	350 4x4	AC70						3425	3425
366	366 4X4, FIS	AC 70			3400	3400	3400	3400	3425
400	400M 4x4, 400 DVX	K427, K430	3500	3500	3500				
	400M 4x4	K427	3500	3500	3500				
	400 4X4	AC70					3200		
425	425 4x4, FIS	A90						3600	3600
450	400A 4x4	K425	3250	3250	3250				
	450 4x4 FIS,TRV	AC90					3500	3500	3500
	XC	AC90						3600	3600
500	500A 4x4, 500M 4x4	M410, M412	3000	3000	3000	3000			
550	550 H1,4X4, FIS,TRV Prowler	0550A				3150	3150	3150	3150
650	650A H1, 4X4 Mud Pro, FIS	0650A	3225	3225	3225	3225	3225	3225	
	650A V-2	VF650	3250						
700	EFI 4X4	P414	2925	2925	2925				
	H1 4X4	0700A			3150	3150			
	Prowler	0700A			2850	2850	2850		
	FIS	0700A				2850	2850	2850	
	TBX,TRV, Cruiser	0700A					3000		
	TBX, TRV, Cruiser, Prowler	0700A						3250	3250
	Mud Pro	0700A					3325	3325	3325
	Diesel 4x4, FIS	LDW		2200	2200		1800	1800	1800
1000	H2 4X4	0950T1			3450	3450			
	Prowler	0950T					3250	3490	3490
	1000 4x4 FIS	0950T					3450	3450	3450
	1000 4x4 TRV, Mud Pro, Cruiser	0950T					3250	3250	3250
	Wildcat	0950T							3410

BOMBARDIER / CAN-AM ATVs / ROVs									
Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			2006	2007	2008	2009	2010	2011	2012
50	DS 50	DS50	3500	3500					
70	DS 70	DS 70			3500	3500	4000	4000	4000
90	DS 90 2 Stroke	DS 90 2	3315	3315					
	DS 90 4 Stroke	DS 90 4	3750	3750	3500	3500	4000	4000	4000
175	Rally	Rotax 175	4100	4100					
250	DS 250 4 Stroke	DS 250 4	3250	3250	3250	3250	3050	3050	3050
400	Outlander 400	Rotax 400	3500	3500	3500	3500			
	Outlander EFI	Rotax 400			3625	3625	3750	3750	3750
450	DS 450	DS 450			2950	2950	3950	3950	3950
500	Renegade 500	Rotax 490		3750	3750	3750	3700	3850	3850
	Outlander 500	Rotax 490		3750	3750	3750	3700	3850	3850
650	DS 650	Rotax 654	3250	3250					
	Outlander 650	Rotax 660	3750	3750	3750	3750	3850	3850	3850
800	Outlander 800	Rotax 810	3500	3500	3500	3500	3625	3625	3500
	Renegade G2 800	Rotax 810							3500
	Renegade 800	Rotax 810		3500	3500	3500	3625	3625	
	Commander	Rotax 810							3625 3625
1000	Commander	Rotax 1010							3500 3500
	Outlander	Rotax 1010							3500
	Renegade	Rotax 1010							3500

Updated March 12, 2012

Copyright 2012 Motorcycle Industry Council

Cut on line above and fold in half. Staple to back flap of MIC Sound Test Manual.

HONDA MOTORCYCLES

Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			Model Year						
			2006	2007	2008	2009	2010	2011	2012
50	CRF50F	AE03E	4250	4250	4250	4250		4250	4250
70	CRF70F	DE02E	4000	4000	4000	4000		4000	4000
80	CRF80F	HE01E	5000	5000	5000	5000		5000	5000
85	CR85R*/RB*	HE07E	6000	6000					
100	CRF100F	HE03E	4750	4750	4750	4750		4750	4750
125	CR125R*	JE01E	5750	5750					
150	CRF150F	KE02E	4250	4250	4250	4250			4250
	CRF150R*/RB*	KE03E		6250	6250	6250			6250
230	CRF230F	ME09E	4000	4000	4000	4000			4000
250	CR250R*	ME03E	4000	4000					
	CRF250R*	ME10E	5500	5500	5500	5500	5500	5500	5500
	CRF250X	ME11E	4500	4500	4500	4500			4500
450	CRF450R*	PE05E	4500	4500	4500	4250	4250	4250	4250
	CRF450X	PE06E	3750	3750	3750	3750			3750
650	XR650L	RD06E	3000	3000	3000	3000			3000
	XR650R	RE01E	3250	3250					

* Not certified to meet the federal EPA noise regulations for newly manufactured off-highway motorcycles.

HONDA ATVs / ROVs (Cont.)

Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			Model Year						
			2006	2007	2008	2009	2010	2011	2012
350	TRX350FE/FM	TE25E	3250						
	TRX350TE/TM	TE24E	3250						
400	TRX400EX/X	TE23E	3500	3500	3500	3500			3500
	TRX400FA/FGA	TE29E	3250	3250					
420	TRX420FA/FPA	TE37E							3250 3250 3250
	TRX420FE/FM/FPE/FPM	TE35E		3000	3000	3000	3000	3000	3000
	TRX420TM/TE	TE34E		3000	3000	3000	3000	3000	3000
450	TRX450R	TE32E	3750	3750	3750	3750			3750
500	TRX500FA/FGA/FPA	TE26E	3250	3250	3250	3250	3250	3250	3250
	TRX500FE/FM/TM/PE/FPM	TE31E	3000	3000	3000	3000	3000	3000	3000
680	TRX680FA/FGA	TE33E	3000	3000	3000	3000	3000	3000	3000
700	TRX700XX	TE36E			3000	3000			
	MUV700	VE01E						2750	2750 2750

HONDA ATVs / ROVs

Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			Model Year						
			2006	2007	2008	2009	2010	2011	2012
90	TRX90/TRX90X	TE18E	3750	3750	3750	3750			3750
250	TRX250EX/X	TE27E	3500	3500	3500	3500			3500 3500
	TRX250TM/TE	TE21E	3250	3250	3250	3250			3250 3250
300	TRX300EX/X	TE19E	3500	3500	3500	3500			

HUSABERG MOTORCYCLES

Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			Model Year						
			2006	2007	2008	2009	2010	2011	2012
250	TE 250	548							3750
300	TE 300	549							3550
390	FE 390	805							3000
570	FE 570 S, FS 570	812							3400
450	FE 450*, FX 450*	812							4500

Note: Sound test RPM not available for prior model years for Husaberg.

Updated March 12, 2012

Copyright 2012 Motorcycle Industry Council

Cut on line above and fold in half. Staple to back flap of MIC Sound Test Manual.

KAWASAKI MOTORCYCLES

Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			Model Year						
			2006	2007	2008	2009	2010	2011	2012
50	KDX50-A6	A102	2500						
65	KX65-A6-9-A-B-C*	KX065AE	6250	6250	6250	6250	6250	6250	6250
85	KX85-A6-9-A-B-C, KX85-B6-7-A*	KX085AE	6000	6000	6000	6000	6000	6000	6000
100	KX100-D6-9-A-B-C*	KX100CE	5750	5750	5750	5750	5750	5750	5750
110	KLX110-A6-9-A KLX110-CA-B-C, KLX110-DA-B-C	LX110AE LX110AE	3500	3500	3500	3500	3500	3500	3500
125	KLX125-A6,B6 KX125-M6*	F445 KX125ME	4000 5750						
140	KLX140-A8-9-A-B-C, KLX140-B8-9-A-B	LX140AE			4000	4000	4000	4000	4000
200	KDX200-H6	DX200HE	3500						
250	KX250-R6-8* KX250-T6-8* KX250-W9-A* KX250-YB-C* KX250-XA* KLX250-T9-A-B-C KLX250-W9-A KL250-G6-7-9-A	KX250RE KX250TE KX250WE KX250YE KX250XE LX250DE LX250DE KL250GE	4500 5750 4000	4500 5750 4000	4500 5750 4000	 4250	 4250	 4250	 4250
300	KLX300-A6-7	LX300AE	3500	3500					
450	KX450-D6-8* KX450-E9-A-B* KX450-FC* KLX450-A8-9-A-B-C	KX450DE KX450EE LX450AE	4250 3750	4250 3750	4250 3750	 3750	 3750	 3750	 3750
650	KL650-A6-7 KL650-E8-9-A-B-C	KL650AE KL650AE	3250 3250	3250 3250	 3250	 3250	 3250	 3250	 3250

* Not certified to meet federal EPA noise regulations for newly manufactured off-highway motorcycles.

KAWASAKI ATVs / ROVs

Engine Size (in cc)	Model	Engine Prefix	Test RPM									
			Model Year									
			2006	2007	2008	2009	2010	2011	2012			
50	KSF50-A6	A110	2500									
	KSF50-B7-9-A-B-C	WA10		3750	3750	3750	3750	3750	3750	3750	3750	
80	KSF80-A6	C113	3500									
90	KSF90-A7-9-A-B-C	WA20		3750	3750	3750	3750	3750	3750	3750	3750	
250	KLF250-A6-9-A-B-C	LF250AE	3500	3500	3500	3500	3500	3500	3500	3500		
300	KVF300-CC	WA60									3750	
360	KVF360-A6-9-A-B-C KVF360-B6-9	VF360AE VF360AE	3500 3500	3500 3500	3500 3500	3500 3500	3500 3500	3500 3500	3500 3500	3500 3500	3500 3500	
	KVF360-C6-9-A-B-C	VF360AE	3500	3500	3500	3500	3500	3500	3500	3500	3500	
450	KSF450-B8-9-A-B-C	SF450BE			3750	3750	3750	3750	3750	3750	3750	
650	KVF650-D6-9-A-B-C KVF650-E6-9 KVF650-F6-9-A-B-C KVF650-G6-9-A-B KVF650-H7-8	VF650AE VF650AE VF650AE VF650AE VF650AE	3250 3250 3750 3750 3750	3250 3250 3750 3750 3750	3250 3250 3750 3750 3750	3250 3250 3750 3750 3750	3250 3250 3750 3750 3750	3250 3250 3750 3750 3750	3250 3250 3750 3750 3750	3250 3250 3750 3750 3750		
700	KSV700-A6-9 KSV700-B6-8-A KSV700-C6 KVF700-A6 KVF700-D6	SV700AE SV700AE SV700AE VF700AE VF700AE	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250		
750	KRF750-G9, H9, J9, K9, L9, M9 KRF750-NA-B-C, KRF750-PA-B-C, KRF750-RA-B-C, KRF750SA-B-C, KRF750TB, KRF750VB-C	VF750DE VF750DE				3250	3250	3250	3250	3250	3250	
	KRT750-AC, KRT750-BC, KRT750-CC, KRT750-DC	VF750DE									3500	
	KVF750-A6-7 KVF750-B6-7 KVF750-C6-7 KVF750-D8-9-A-B, E8-9-A KVF750-F8-A-B KVF750-GC, HC, JC, LC	VF750AE VF750AE VF750AE VF750DE VF750DE VF750DE	3250 3250 3250 3250 3250	3250 3250 3250 3250 3250	 3250 3250	 3250 3250	 3250 3250	 3250 3250	 3250 3250	 3250 3250	 3250 3250	

Updated March 12, 2012

Copyright 2012 Motorcycle Industry Council

Cut on line above and fold in half. Staple to back flap of MIC Sound Test Manual.

KTM MOTORCYCLES										KTM MOTORCYCLES (Cont.)										
Engine Size (in cc)	Model	Engine Prefix	Test RPM							Engine Size (in cc)	Model	Engine Prefix	Test RPM							
			2006	2007	2008	2009	2010	2011	2012				2006	2007	2008	2009	2010	2011	2012	
50	50 Jr/Sr Adventure*	450	4800	4800						450 (cont.)	450 XC-W Six Days*	780						3400		
	50 SX Pro Jr*, SX Mini*, 50 SX *	450,452	5100	5100	5100	5100	5100	5100	5100	500	EXC*	787							4400	
	50 SX Pro Sr*	451	5100	5100	5100	5100	5100				XC-W*	787							4350	
65	65 SX*	460,462	4750	4750	4750	4750	4750	4750	4750	505	505 SX-F*, XC-F*	773		4625	4625	4625				
	65 XC*	460			4500	4500					505 SX*	592		4600	4600					
85/105	85 SX*, 105 SX*	490,470, 475,BET	4725	4725	4725	4750	4750	4750	4750	525/530	SX*, XC Racing*, SMC*	590	4600	4600	4600	4600				
	85 XC*, 105 XC*	490			4450	4450					EXC, XC-W*	590,786		3380	3380	3380	3380	3380		
125	125 SX*	503	5600	5600	5600	5600			5600	560	560 SMR*	590	4600	4600						
144/150	144 SX*, 150 SX*, 150 XC*	515		5200	5200	5200	5200	5200	5200	625	625 SMC*	584	3450							
200	200 EXC*, XC*, XC-W*	523	4000	4000	4000	4000	4000	4000	4000	640	LC4 Adventure, LC4 Supermoto	584	3450							
250	250 SX*	546,548	3750	3750	3750	3750	3750	3750	3750	690	SM, Enduro, Duke, SMC			3425	3425	3425	3425			
	SX-F*	770,771	5200	5200	5200	5200	5200	5200	5200		SM, Enduro, Duke, SMC	765						3425		
	XC-F*, XC-F-W*	770,771		4800	4800	4800	4800	4800	4800		Enduro R	753							3500	
	XC*, XC-W*	548	3750	3750	3750	3750	3750	3750	3750	950	Adventure, Adventure S, Supermoto, Super Enduro	600	4750	4750	4750	4750				
	XCF-W*	774							5800	990	Adventure, Adventure S, Super Duke, Super Duke R	600,601		4750	4750	4750	4750	4750	4750	
300	300 EXC*	547	3550	3550	3550	3550					Super Moto R, Supermoto T	626						4500	4500	
	XC*, XC-W*	556,549	3550	3550	3550	3550	3550	3550	3550	1190	RC8, RC8 R	612,693			4750	4750	4750	4750	4750	
350	SX-F, XC-F*	772							5000											
	EXC-F	775																	4300	
	XCF-W*	775																	5900	
400	400 EXC Racing*	595	4625							KTM ATVs										
	400 XC-W*	595	4625	4625		4625	4625													
450	450 SMR*, SMC*	595,773	4625	4625	4625				4625	Engine Size				Test RPM						
	450 EXC	595,780		3400	3400	3400	3400	3400		(in cc)	Model	Prefix	2006	2007	2008	2009	2010	2011	2012	
	450 EXC Racing*, SX*, SX-F*, XC*, XC Racing*, XC-W*	595,773	4625	4625	4625	4625	4625	4625	4625	450	XC-ATV	830			3400	3400				
	XC-W*	781							4200	450	SX-ATV	835				3800				
	SX-F* Factory Ed.	789							4750	505	SX-ATV	836				3600				
										525	XC-ATV	831			3400	3400				

* Not certified to meet the federal EPA noise regulations for newly manufactured off-highway motorcycles.

Updated March 12, 2012

Copyright 2012 Motorcycle Industry Council

Cut on line above and fold in half. Staple to back flap of MIC Sound Test Manual.

KYMCO ATVs / ROVs									
Engine			Test RPM						
Size		Engine	Model Year						
(in cc)	Model	Prefix	2006	2007	2008	2009	2010	2011	2012
50	Mongoose 50	LA10		3750	3750	3750			
70	Mongoose 70	LA15		3750	3750	3750			3750
90	Mongoose 90	LA20		3750	3750				
	Mongoose 90 R	LA20				3750	3750	3750	3750
150	MXU 150	LA30		3875	3875	3875	3875	3875	3875
250	Mongoose 250	LA50		3500	3500	3500			
	MXU 250	LB50		3500	3500	3500			
300	Mongoose 300	LA60		3750	3750	3750	3750	3750	3750
	MXU 300	LB60		3750	3750	3750	3750	3750	3750
375	MXU 375	LA70			3250	3250	3250	3250	3250
	Maxxer 375	LB70					3250	3250	3250
450	MXU450i	LC90							3750
	Maxxer 450i	LC90							3750
500	MXU 500, MXU 500 IRS	LAA		3250	3250	3250	3250	3250	3250
	MXU 500i	LDA							3250
	UXV 500 (ROV)	UAA				3250	3250	3250	3250
	UXV 500i (ROV)	UBA							3250

POLARIS ATVs / ROVs									
Engine			Test RPM						
Size		Engine	Model Year						
(in cc)	Model	Prefix	2006	2007	2008	2009	2010	2011	2012
50	Predator 50-2 Stroke	AR03-01	3000						
	Predator 50-4 Stroke	RF3KA05		3750					
	Scrambler 50-2 Stroke	AR03-01	3000						
	Outlaw 50-4 Stroke	RF3KA05			3750	3750	3750	3750	3750
90	Outlaw 90-4 Stroke	RF3KA09		4000	4000	4000	4000	4000	4000
	2 Stroke	AR07	3000						
	Sportsman 90-2 Stroke	AR07	3000						
	Sportsman 90-4 Stroke	RF3KA09		4000	4000	4000	4000	4000	4000
170	RZR 170	AC11				3500	3500	3500	3500
200	Phoenix 200	V39	3750	3750	3750	3750	3750	3750	3750
	Sawtooth 200	V39	3750	3750					
250	Trail Blazer	EC25PFE15	3000						

POLARIS ATVs / ROVs (Cont.)									
Engine			Test RPM						
Size		Engine	Model Year						
(in cc)	Model	Prefix	2006	2007	2008	2009	2010	2011	2012
300	Hawkeye 300	ES30P	3375	3375					
	Sportsman 300	ES30P			3375	3375	3375	3375	
330	Magnum 330 2X4	ES32P10	3375						
	Magnum 330 4X4	ES32P10	3375						
	Trail Boss 330	ES32P10	3375	3375	3375	3375	3375	3375	3375
	Trail Blazer 330	ES32P10			3375	3375	3375	3375	3375
400/450	Outlaw 450 MXR	ES051KLE			4250	4250	4250		
	Sportsman 400 / 450	EH460PLE	3250	3250	3250	3250	3250	3250	3250
	Ranger 400	EH460PLE					3250	3250	3250
500	ATP 500	EH50P20	3250						
	Predator 500	ES50P01	4000	4000					
	Outlaw 500	ES50P04	4000	4000					
	Scrambler 500 4x4	EH50P04	3150	3150	3150	3150	3150	3250	3250
	Sportsman 500 EFI / 500 EFI Touring / 500 EFI X2	EH50P21	3250	3250	3250	3250	3250	3250	3250
	Sportsman 500 H.O.	EH50P13	3150		3150	3150	3150	3250	3250
	Sportsman 500 6x6	EH50P10	3000	3000	3000				
	Ranger 500	EH500PLE			3000	3000	3000	3000	3000
525	Outlaw 525	ES051KLE		4000	4000	4000	4000	4000	
550	Sportsman 550 Touring	ES550PLE						3250	3250
	Sportsman 550 X2	ES550PLE						3250	3250
	Sportsman 550	ES550PLE				3250	3250	3250	3250
570	RZR 570	ES057OLE							3500
700	Ranger 700	EH680PLE	2750	2750	2750	2750			
	Sportsman 700 EFI / EFI Touring	EH680PLE	3000	3000	3000				
800	Sportsman 800 / 800 X2 / 800 Touring	EH076OLE	3000	3000	3000	3000	3000	3150	3150
	Sportsman 800 6x6	EH076OLE					2875	2875	3050
	Ranger 800 6x6 / 800 HD / 800 Crew	EH076OLE						2875	2875
	Ranger 800 XP	EH076OLE						2950	2950
	RZR 800	EH076OLE			3050	3050	3050	3050	3050
	RZR S / S4	EH076OLE					3150	3150	3150
850	850 Touring / 850 x2	EH0850LE					3500	3500	3500
875	RZR XP	ES0870LE						4125	4125
	RZR XP4	ES0870LE						4125	4125

Updated March 12, 2012

Copyright 2012 Motorcycle Industry Council

Cut on line above and fold in half. Staple to back flap of MIC Sound Test Manual.

SUZUKI MOTORCYCLES

Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			2006	2007	2008	2009	2010	2011	2012
50	JR50	A102	2500						
65	RM65*	KX65B	6250						
70	DR-Z70	B401			4000	4000	4000		
85	RM85*, RM85L*	D107	6000	6000	6000	6000	6000	6000	
110	DR-Z110	LX110A, LX110BE	3500						
125	DR-Z125, DR-Z125L	F445	4000	4000	4000	4000	4000	4000	4000
	RM125*	F134	5750	5750	5650				
200	DR200SE	H402	4250	4250	4250	4250	4250	4250	4250
250	DR-Z250	J428	4000	4000					
	RM-250*	J119	4000	4000	4000				
	RM-Z250*	KX250NE, J442	5500	5500	5500	5500			
	RM-Z250*	J445					5750	5750	5750
400	DRZ400/E	K417, K419	4000	4000					
	DRZ400S/E, DRZ400S/SM	K419	3750	3750		3750	3750	3750	3750
450	RM-Z450/Z*	L401, L405	4500	4500	4500	4500	4500	4500	4500
	RMX450Z	L407					3250	3250	
650	DR650SE	P409	3250	3250	3250	3250	3250	3250	3250

* Not certified to meet the federal EPA noise regulations for newly manufactured off-highway motorcycles.

SUZUKI ATVs

Engine Size (in cc)	Model	Engine Prefix	Test RPM						
			2006	2007	2008	2009	2010	2011	2012
50	LT50, LT-A50	A110	2500						
	LT-Z50/Z* QuadSport Z50	AZ413, Z402	2550	2550	2550	2550	2550		
80	LT80 QuadSport 80	C113	3500						
90	LT-Z90/Z QuadSport Z90	D402		3500	3500	3500	3500		
250	LT-F250 Ozark	J434	3500	3500	3500	3500	3500	3500	3500
	LT-Z250 QuadSport	J437	3500	3500	3500	3500	3500	3500	
400	LT-A400/F Eiger	K420, K421	3250	3250					
	LT-F400/F Eiger	K422, K423	3500	3500					
	LT-A400/ F/FC/FQ/FZ/ (F1) KingQuad/AS	K433, K434, K438, K439				3250	3250	3250	3250
	LT-F400/F/FC/FQ/ KingQuad /FS	K435, K436			3500	3500	3500		
	LT-F400/F/FZ/ (F1) KingQuad	K440, K441						3250	3250
	LT-Z400/Z QuadSport 400	K428, K437	3500	3500	3500	3500	3500	3500	3500
450	LT-R450/Z QuadRacer R450	L402, L404	3750	3750	3750	3750	3750		
	LT-A450X/XC KingQuad 450	L403		3250	3250	3250	3250		
500	LT-F500F Vinson	M411	3250	3250					
	LT-A500F Vinson	M409	3000	3000					
	LT-A500X/XP/ XPC/XPW/XPZ/XZ KingQuad	M413						3250	3250
700	LT-A700Z KingQuad	P413	3000	3000					
	LT-V700F Twin Peaks	VF700AE	3250						
750	LT-A750X KingQuad	R701			3000				
	LT-A750X/XC/XR/ XZ/XP/XPC/XPZ KingQuad	R407					3250	3000	3000

Updated March 12, 2012

Copyright 2012 Motorcycle Industry Council

Cut on line above and fold in half. Staple to back flap of MIC Sound Test Manual.

TOMBERLIN ATVs										YAMAHA ATVs /ROVs										
Engine			Test RPM								Engine			Test RPM						
Size		Engine	Model Year								Size		Engine	Model Year						
(in cc)	Model	Prefix	2006	2007	2008	2009	2010	2011	2012	(in cc)	Model	Prefix	2006	2007	2008	2009	2010	2011	2012	
150	SDX150	AAVIX.150AAL		3225						50	YFM50	A303E	4000	4000	4000	4000				
200	SDX200	AAVIX.200AAL		3350				3350		80	YFM80	B302E, B304E	3750	3750	3750					
300	SDX300	BAVIX.300AAL		3300		3300			3300	90	YFM90	B306E				4000	4000	4000	4000	
600	SDX600	BAVIX.552ACL						3200		125	YFM125A	E365E	3500	3500	3500	3500	3500	3500	3500	
											YFM 125R	E3G4E						4000	4000	
										200	YFS200	G109E	3500							
										250	YFM250R	G369E			3500	3500	3500	3500	3500	
											YFM250	G302E, G334E	3500	3500	3500	3500	3500	3500		
										300	YFM300	H331E							3250	
										350	YFM350FX	H306E	3500							
50	PW50	3PT	3750	3750	3750	3750	2750		2750		YFZ350	3GG	3750							
	TTR50E	A305E	4250	4250	4250	4250		4250	4250		YFM350FWA/ FWAN	H315E	3250	3250	3250	3250	3250	3250	3250	
80	PW80	3RV	3750								YFM350A/AS	H316E	3250	3250	3250	3250	3250	3250		
85	YZ85*	B118E	6000	6000	6000	6000	6000	6000	6000		YFM350	H318E, H315E	3500	3500	3500	3500	3500	3500	3500	
90	TTR90/E	B305E	3500	3500						400	YFM400FWAN	J320E	3500	3500	3500	3500	3500			
110	TTR110	5B6			3750	3750	3750	3750	3750		YFM400FWN	H310E	3500	3500	3500	3500	3500	3500		
125	TTR125/E/ L/LWE	E349E	4000	4000	4000	4000	4000	4000	4000		YFM450FWAN/F AS/ FWAD	J310E	3125	3125	3125	3125	3125	3125	3125	
	TTR125LW	E309E		4000	4000					450	YFZ450	J325E	3750	3750	3750	3750			3750	
	YZ125*	E118E, E120E	5750	5750	5750	5750	5750	5750	5750		YZF450R	J327E				3720	3750	3750	3750	
200	TW200	3AW	3500	3500	3500	3500	3500	3500	3500		YXR450F Rhino	J322E	3000	3000	3000	3000	3000			
225	XT225	4BE	4000	4000							YFM550FWA/ FWAD	J328E				3125	3125	3125	3125	
	TTR225	G331E	3750							660	YFM660FWA	M302E, M303E	3125	3125	3125	3125				
230	TTR230	G341E		3750	3750	3750		3750	3750		YXR660F Rhino	M305E	3000	3000						
250	TTR250	G307E	3750							700	YFM700R	M308E	3125	3125	3125	3125	3125	3125	3125	
	XT250	G374E			3750	3750	3750	3750	3750		YFM700FWA/ FWAD	M310E			3125	3125	3125	3125	3125	
	WR250F	G348E, G356E	3250	3250	3250	3250	3250	3250	3250		YXR700 Rhino	M312E			2625	2625	2625	2625	2625	
	WR250R	G375E			4500	4500	4500		4500		YXR700F4	M314E					2625			
	WR250X	G37E			4500	4500	4500													
	YZ250*	G111E	4250	4250	4250	4250	4250	4250	4250											
	YZ250F*	G342E, G357E	5250	5250	5250	5250	5250	5250	5250											
450	WR450F	J321E, J326E, J332E	3250	3250	3250	3250	3250	3250	3250											
	YZ450F*	J324E, J329E	4500	4500	4500	4500	4500	4500	4500											
1200	XT1200	P403E							3625											

* Not certified to meet the federal EPA noise regulations for newly manufactured off-highway motorcycles.

Updated March 12, 2012

Copyright 2012 Motorcycle Industry Council

Cut on line above and fold in half. Staple to back flap of MIC Sound Test Manual.